VCC-2™ USB Desktop Station

Standard Features

- USB desk console, compatible with Motorola, SmartPTT & TRBOnet Dispatch Software
- Single channel of quality 2-way audio
- Integrates with Plantronics PTT headsets
- Foot switch & PTT handset functionality
- Left & right level controls for connected Stereo PC speakers
- PTT button provides "hot key" sequence, for mouse free operation
- 13" gooseneck microphone
- Rugged, compact design



Overview

The VCC-2[™] is a USB Desk Console designed for use with popular software dispatch consoles

The VCC-2™ has unique features geared for use in public safety. Features include: ports for integration with commonly available: Plantronics PTT headsets, PTT handset, footswitch and built in gooseneck microphone. The VCC-2 provides intuitive controls for speaker volume, & PTT. The large PTT button provides a 'hot key' sequence to the software application to actuate press to talk functions. The 'hot key' sequence can be factory customized upon request. The VCC-2 utilizes Windows™ standard USB audio drivers, making installation a breeze.

The VCC-2 is an easy to setup & easy to use interoperability tool with high quality audio, numerous integration features and it is half the size of the VCC-3.

Technical Specifications

- Frequency Response: 200Hz- 9kHz
- Distortion: < .1%
- Analog output range: -40 dB to +3 dB
- Headset/Handset Impedance: Rx-10kOhm, Tx - 50 Ohm
- RJ-25 for PTT headset/handset connectivity
- USB 'B' style connector & USB powered
- 3.5 mm jacks for PC speaker & foot pedal connectivity
- 350mA Nominal Current Consumption
- Size: 6.25" W x 2" H x 8" D
- Weight: 20 ounces
- 6 BTUs Per Hour Output

A Veteran Owned Small Business