



VCC-3 USB Microphone Command Console



VCC-3 Microphone Command Console

ETC New USB Programmer App allows User
Defined PTT action




Accessories



A150 AC Powered Stereo Speakers

Actual Style may change



Mono Headset with MBP-18 Belt Pack



FP-115P Plug in PTT Foot Pedal



FP-117P Plug in PTT Foot Pedal



PTT 6 Wire Handset / 6' modular coil cord

Standard Features

- USB Command Console, integrates with the Soft Dispatch systems from Motorola Solution, SmartPTT, iNemsoft, *TRBOnet*, Skytec, and others.
- Single 2-way audio talk channel.
- Switch between Headset or Microphone and or user telephone at the touch of a button.
- ETC Foot switch & PTT handset functionality
- Top mounted Left & Right Volume controls to control the Stereo speakers audio.
- User Defined PTT action with **ETC USB Programmer App**
- PTT using Keyboard “Hot Key” or “Joy Stick” HID mode for mouse free operation.
- 18” Close Talking Gooseneck Microphone.
- Rugged Steel designed enclosure.

Technical Specifications

- Frequency Response: 300Hz- 10kHz
- Distortion: < .1%
- Analog output range: -40 dB to +8 dB
- Headset/Handset Impedance: Rx-10kOhm, Tx - 50 Ohm
- USB ‘B’ style connector & USB powered
- 3.5 mm jacks for PC speaker & foot pedal connectivity
- 350mA Nominal Current Consumption
- Size: 6.25” W x 2” H x 8” D
- Weight: 42 ounces
- BTUs Per Hour Output