VCC-2 USB mini-Microphone Console






VCC-2 USB mini-Microphone Console

ETC New USB Programmer App allows User Defined PTT action



VCC-2 USB mini-Microphone Console

Accessories





A150 AC Powered Stereo Speakers

Actual Style may change



Mono Headset with MBP-18 Belt Pack



FP-115P Plug in PTT Foot Pedal



FP-117P Plug in PTT Heavy Duty Foot Pedal



TH-3PTT 6 Wire Handset / 6' modular coil cord

Standard Features

- USB Microphone console, designed to operate with the Soft Dispatch Systems from Motorola Solutions, , SmartPTT, iNemsoft, TRBOnet, Skytec, Hytera and others
- Single 2-way audio talk channel
- Integrates with Plantronics Mono headsets
- PTT Foot switch & PTT handset functionality
- Left & Right Volume controls for connected Stereo PC speakers
- PTT button provides "hot key" or "Gamer" sequence, for mouse free operation
- 18" Close Talking Gooseneck Microphone
- Made of Rugged Metal in a compact design
- Rear mounted DIP Switch for selectable operation, Microphone or Headset

Technical Specifications

- Frequency Response: 200Hz -10kHz
- Distortion: < .1%
- Analog output range: -40 dB to +3 dB
- Headset/Handset Impedance: Rx-10kOhm, Tx - 50 Ohm
- RJ-25 for PTT headset/handset connectivity
- USB 'B' style connector & USB powered
- 3.5 mm jacks for PC speaker & foot pedal connectivity
- 350mA Nominal Current Consumption
- Size: 6.25" W x 2" H x 8" D
- Weight: 20 ounces
- 6 BTUs Per Hour Output

